



#### ERZ-HPA-0175-0625-43

The ERZ-HPA-0175-0625-43 is a High Power Amplifier providing an output power of 43 dBm with a gain of 43 dB. The compact size and modularity makes it ideal for a wide range of applications.

### High Power Amplifier ERZ-HPA-0175-0625-43

#### Main Features:

- Frequency Range: 1.75 to 6.25 GHz.
- Typical values: Psat 43 dBm, Gain 43 dB
- RF connectors (I/O): SMA Female
- D-sub 9 connector for DC connection
- Several mounting options
- Gold platted compact aluminum housing
- Hi-reliability and dedicated screening/ environmental tests available under request

#### Typical applications:

- Industrial / Laboratory
- Satcom / Telecom
- Space / Aerospace / Military

Parameter	Value		Units	
	Min	Тур	Max	
Frequency	1.75	-	6.25	GHz
Output Power (Psat)	41	43	45	dBm
Small Signal Gain	40	43	46	dB
Gain Flatness	-	±1.25	-	dB
Noise Figure	-	-	-	dB
VSWR input	1.0:1	1.3:1	1.8:1	-
VSWR output	1.2:1	1.8:1	2.5:1	-
Switch ON/OFF time	-	150/350	-	ns
DC Voltage	24	28	32	V
Power Consumption (@Psat)	-	105	-	W

Performance

Specifications at a case temperature of 25°C



#### **Output Power**

Figure 1 shows saturated output power measurement as a function of frequency at room temperature (25°C).






Figure 1: ERZ-HPA-0175-0625-43 Psat

Figure 2 shows output power Vs input power measurement at room temperature (25°C).





Tel: +34 942 29 13 42



#### **Power Gain**

Figure 3 shows the power gain at Psat measurement as a function of frequency at different temperatures.





Figure 3: ERZ-HPA-0175-0625-43 PowerGain

#### Gain Vs Input Power

Figure 4 shows gain measurement Vs input power at different frequencies.



Tel: +34 942 29 13 42



#### Small Signal Gain

Figure 5 shows the small signal gain measurement as a function of frequency at room temperature ( $25^{\circ}$ C).




Figure 5: ERZ-HPA-0175-0625-43 Small Signal Gain

#### Gain Flatness over Frequency & Temperature

Figure 6 shows small signal gain flatness over frequency and temperature at -40°C, 25°C and 70°C.




Figure 6: ERZ-HPA-0175-0625-43 Small Signal Gain over temperature

Tel: +34 942 29 13 42



#### Input Matching

Figure 7 shows input VSWR as a function of frequency at room temperature (25°C).




Figure 7: ERZ-HPA-0175-0625-43 Input Matching

#### **Output Matching**

Figure 8 shows output VSWR as a function of frequency at room temperature (25°C).




Figure 8: ERZ-HPA-0175-0625-43 Noise Figure

Tel: +34 942 29 13 42



ERZ-HPA-0175-0625-43

#### **Mechanical Specifications**

Parameter	Value	Units
Dimensions	125x95x22 (LxWxH)	mm
Weight	475 +/-10%	grams
RF Connectors	IN/OUT: SMA (F)	-
DC & Control Connector	D-sub 9 Male	-

#### **Outline Drawing**




Figure 9: ERZ-HPA-0175-0625-43 Outline Drawing



## **High Power Amplifier**

ERZ-HPA-0175-0625-43

#### DC & Control Interface

Power supply characteristics

• Input Voltage: 28 ±4 VDC

Control characteristics

- TTL command (ON/OFF function).
- Output Power, temperature and current monitoring.

Table below shows D-sub 9 connector (Male) pinout:




Figure 10: D-sub 9 Connector (Front view)

PIN	SIGNAL	DESCRIPTION
1	Output Power Monitor	
2	NC	Not Connected
3	Current Sensor	Vo= 0.1V/A
4	Temperature Monitor	Vo = -11.69 mV C × T + 1.8663 V
5	Enable	TTL Signal OFF (0V to 0.8V); ON (2V to 5.5V)
6	+28V	+28 VDC
7	+28V	+28 VDC
8	GND	Ground
9	GND	Ground



ERZ-HPA-0175-0625-43

#### Absolute Maximum Ratings

Condition	Value
Maximum DC Voltage	+32 VDC
Maximum RF Input Power	17 dBm
Operation temperature (at case)	-40° to 85 °C
Storage temperature	-55° to 125 °C

- Stress above these ratings may cause permanent damage to the device.
- It is final user responsibility to maintain the amplifier within the specified ranges.

#### **Measurements Conditions**

All measurements provided in this report were performed at the following conditions:

Condition	Value	
Temperature (DUT ON)	-40°C, 25 °C, 85 °C ± 1°C	
Humidity	44% ± 10%	
DUT Warm up time	30 min	
DUT minimum operation time	24 hours	
Test equipment warm up time	2 hours	
Additional temperature cycles in climatic chamber (DUT OFF)	-40°C to 70°C	

#### **Environmental Specifications (By Design)**

Operating Temperature:	-40 to +85 °C	(MIL-STD-810F, method 520.2)
Storage Temperature:	-55 to +125 °C	(MIL-STD-810F, method 520.2)
Vibration:	8g rms	(MIL-STD-810F, method 514.5)
Shock:	20g,11ms,saw-tooth	(MIL-STD-810F, method 516.5)
Acceleration:	15g	(MIL-STD-810F, method 513.5)

#### **RoHS & REACH Compliance**

This part is compliant with EU 2011/65/UE RoHS (Restrictions on the Use of Certain Hazardous Substances in Electrical and Electronic Equipment) and REACH (Registration, Evaluation, Authorization and restriction of Chemical substances) directives.



Tel: +34 942 29 13 42

sales@erzia.com

www.erzia.com



# High Power Amplifier

ERZ-HPA-0175-0625-43

#### **Documentation and Test Reports**

All modules are at least delivered with: Electrical Test Report, Certificate of Conformance, Certificate of Acceptance and Origin. Optionally, units can be environmentally tested (temperature, vibration...).

#### **Option (HS): Heat Sink**

A heat sink (HS) can be provided to allow the operation of Power Amplifiers. Please note that most power amplifiers need heat sink or appropriate heat dissipation strategy.


#### Space / Military Usage

Most of ERZIA's products are based on rad-hard technologies and can be manufactured and integrated according to MIL / ECSS or specific hi-rel standard-screening for space, aeronautics, military or specific hi-reliability usage.

#### **Customization and Extended Performances**

ERZIA can fully design or adapt one of the existing RF amplifiers designs according to your specifications. Please contact us for additional information.

#### Model Number Codification



#### MODEL NUMBER

Tel: +34 942 29 13 42

sales@erzia.com

www.erzia.com

# ERZIA

20210408\_rev1.1

Copyright © 2021 ERZIA Technologies. All rights reserved. This information is commercial and indicative, subject to change without notice

Tel: +34 942 29 13 42

sales@erzia.com

www.erzia.com